



Description

The Model 88 is a family of LCD Indicators/Controllers, with eight 7-segment digits that are 0.35" [9mm] in height. The standard display is an LCD backlit display, providing red characters on a dark background. An optional reflective LCD with dark characters on a light background is available. Unit programming is accomplished using four front-panel switches, or programming can be done using the optional serial data interface and dedicated PC-based software (Redi-Ware), which is available from Redington free of charge. Upon power up, the Indicator/Controller performs internal diagnostics and flashes all segments of the display "ON" and "OFF" several times. The Indicator/Controller then configures itself per previous programming, loads the internal Counters and Timers with their values prior to power down, and begins normal operation.

The Model 88 Indicator/Controller is capable of receiving counts and/or analog inputs, processing those inputs in a number of different selectable ways, and then providing outputs in several formats. Base units, i.e.; #8800-0000, or similar units can be programmed for Elapsed Time, Rate, Preset Count/Time, count Add/Add, count Add/Sub., or count Quadrature. The two independent control outputs are open-collector (NPN), outputs that can be controlled by either count inputs, time, the analog input, or combinations of the analog input/time and count inputs. Based on two inputs, the indicator is capable of displaying two counts, a rate indicator and an elapsed time at the same time. The base unit provides the display, programming, and processing functions for the final configuration as well as the counter I/O function. I/O functions and factory installed modules are available that allow the user to configure complex functions into a small enclosure. Other models add analog input/output functions to the base unit, and serial communication functions, which supports RS232/RS422/RS485, providing the user with a broad selection of configurations.

Each Model 88 base unit is normally powered from a DC voltage of +10V to + 32 V. However, an AC power supply module # 200557-002S can be attached to the rear of the unit that converts +90VAC to +250VAC, to +12VDC, which can be used to power the Model 88 and an external sensor. Another module, 200557-001S, can be added that converts the discrete outputs of the Model 88 base unit to relay contacts.

Features

- Dual up counting
- Preset of time, rate or count
- Directional counting
- 1,2,4x quadrature
- Add/add counting
- Add/subtract counting
- Rate indication on count inputs
- Analog ranges: 0 to 10 VDC or 4 to 20 mA
- Prescaling of analog inputs and counts
- Elapsed timer function available for all modes of operation
- NEMA 4X/IP56 sealed panel
- UL, cUL recognized, CE compliant UL file # E19514

Options

- Relay Module 200557-001S  
2 form C, 5 amp relays
- Serial Comm. (RS232, RS422, RS485)
- Analog input/outputs
- Display color
- AC Power Module 200557-002S  
+90 VAC to +285 VAC, 50/60 Hz (unit is normally powered from +10 VDC to +32 VDC)

Specifications

|                             |   |  |
|-----------------------------|---|--|
| <b>Display:</b>             | LCD, 8 digits, 0.35" [9mm] negative image Transmissive Red or Positive image reflective display. In the negative count mode the display will be 7 digits with a - sign. | Three different quadrature resolutions<br>Add-Add<br>Add-Subtract<br>Dual Count<br>Elapsed Time<br>Analog Input<br>Predetermining  |
| <b>Annunciators:</b>        | A, B, R, 1, 2 ANLG, LOCK, HZ, RPM, HRS, SEC. 0.039" [1mm]   |  |
| <b>Programming:</b>         | Programming is accomplished through the front panel switches or by serial data interface and dedicated PC software, supplied by Redington Counters, Inc.                | <b>Predetermining Functions:</b><br>Preset units provide two discrete outputs which can be controlled as a function of Count, Rate, Elapsed Time, or Analog Input. Each control output can be set by any of the four functions and reset by the same or a different function. For example, Control Output 1 could be set when a specific count is reached and reset when an analog input level is reached. |
| <b>Available Functions:</b> | Totalizer<br>Directional Counting<br>Rate/Count   |  |

**Predetermining Timer:  
Programmable Ranges:**

Hours  
Seconds  
Hours, Minutes & Seconds

**Programmable Decimal Point:**

Counter A: 4 decimal point locations may be selected.  
Counter B: 4 decimal point locations may be selected.  
Rate Display: 4 decimal point locations may be selected.  
Analog Input: 4 decimal point locations may be selected.  
Time: 4 decimal point locations may be selected.

**Power Requirements:**

Base unit: +10VDC TO +32VDC @ 50mA max.  
Relay Module: Model 200557-001S; +10VDC to +32VDC @ 50mA, max.  
AC Power Supply: Model 200557-002S; +90VAC to +250 VAC 50/60 Hz @ 6 VA max.

**Memory:** Nonvolatile EEPROM retains all program parameters and values when power is removed. EEPROM provides 20 year data retention.

**Sensor Power:** +12VDC @ 100mA, minimum (200557-002S Module)

**Front Panel Lockout:**

Two front panel lockouts are available. In the programming mode, the operator is prohibited from entering new parameters. In the operating mode, the lockout disallows manual reset of any displayed inputs.

**Count/Timer Inputs (Input A & Input B):**

Software selectable: Switch contact or voltage input  
Software Selectable: Filter: No filter or 160 Hz 1<sup>st</sup> order L.P.  
Voltage Mode  $V_{IH}$ : 2.4VDC, Min.  
Voltage Mode  $V_{IL}$ : 0.8VDC, Max. or open circuit  
Switch Mode  $V_{IH}$ : 2.4 VDC, Min. or open circuit  
Switch Mode  $V_{IL}$ : 0.8VDC, Max.  
Maximum Input Voltage: 32.0VDC  
Minimum Input Voltage: -0.8VDC

**Counter/Timer Operational Format:**

Input A is used for all count functions  
Input B is used for Timer enable and all dual Input counter functions (i.e. ADD/ADD, ADD-SUB, DIRECTIONAL COUNT, QUADRATURE, and DUAL COUNT).

**Input Scaling:** A & B Counters and Analog input, (- 9.9999 to 99.9999)

**Quadrature Counting:**  
Software selectable X1, 2, 4

**Analog Input:** 0 to 10VDC or 4 to 20 mA  
Resolution: 4 digit

**Input Impedence:**  
150K ohms, for 0 to 10VDC  
100 ohms, for 4 to 20 mA

**Max. Count Rate:** 40 KHz for single counter mode.  
20 KHz for dual count modes

**Rate Input Units:** The rate input can be expressed in terms of scaled counts per minute (rP) or scaled counts per second (HZ) of counter A.

**Rate Indicator Accuracy:**

±0.01%, References Time Base @T=25°C

**Minimum Input Frequency:**

1 pulse in 10 sec. for Hz setting. 1 pulse in 60 sec. for RPM setting.

**Maxium Input**

**Frequency:** 40 K HZ

**Reset Functions:** (Automatic & Manual)

**Reset-to-Zero:** Can be programmed so that the output activates when counter equals the preset value, counter returns to zero when reset.

**Reset-to-Preset:** Can be programmed so that the output activates when counter equals zero, Counter returns to Preset value when reset.

**Resets:** Automatic or manual.

**Outputs:** Base unit; Solid-state NPN: (2) Open collector:  $I_{SNK}=100mA$  @  $V_{OL}=1.1VDC$   $V_{OH}=40VDC$

**Relay Module:** Model 200557-001S; 2 form "C" relays Rated @ 5 amps 250 VAC, 30VDC(resistive load) 1/10<sup>th</sup> HP @120VAC (inductive load)

**Relay Life Expectancy:**  
100,000 cycles min. @ max. Rated load.

**Programmable Timed Outputs:**  
Both control outputs can be timed.

**Elapsed Timer Accuracy:** ± 0.01% @T=25°C

**Analog Output:** 0 TO 10VDC OR 4 TO 20mA  
**Accuracy:** 0.25% of full scale @ T = 25°C  
**Resolution:** 14 bits

**RS232/RS485/RS422 Serial Communications: (Optional)**

**Baud rate:** Selectable 2400, 4800, 9600, or 19.2K  
**Data length/Parity/Stop Bits:** 8n1  
**RS485 Address:** Programmable from 0 to 99.  
**Transceiver Loading:** RS232/RS485/RS422- up to 16 loads

**Certifications & Compliances:**

UL, cUL- Recognized Component, file # E 195514  
CE-Compliant to EN 61326: 1998 for industrial equipment

**Environmental Conditions:**

**Operating temperature:** -4°F to +140°F [-20°C to +60°C]  
**Storage temperature:** -40°F to +185°F [-40°C to +85°C]  
**Operating & storage humidity:** to 95% (non-condensing) from -4°F to +140°F [-20°C to +60°C]  
**Altitude:** Up to 6561Ft. (2000 Meters)

**Electrical Connection:** Wire clamping screw terminals

**Construction:**

High impact black plastic case with "Clip" type mount. Front panel meets NEMA 4X/IP65 requirements for indoors use, when properly installed. Oversized front panel flange insures proper sealing of panel cutouts. Gaskets for front panel are provided.

**Panel Thickness:** 0.05" to 0.20" [1.3 to 5.1mm]

**Weight:** Less than 3 oz. (85g)



## Ordering Information

| MODEL NUMBER | DESCRIPTION   | DISPLAY RED TRANSMISSIVE | DISPLAY REFLECTIVE | ANALOG INPUT | ANALOG OUTPUT | RS-485 RS-232 RS 422 |
|--------------|---|--------------------------|--------------------|--------------|---------------|----------------------|
| 8800-0000    | Base unit, Red Trans., +10 to +32VDC, Prescale                        | X                        |                    |              |               |                      |
| 8810-0000    | Base unit, Reflective, +10 to +32VDC, Prescale                        |                          | X                  |              |               |                      |
| 8800-0100    | Red Trans., +10 to +32VDC, Prescale, RS485                            | X                        |                    |              |               | X                    |
| 8810-0100    | Reflective, +10 to +32VDC, Prescale,RS485                             |                          | X                  |              |               | X                    |
| 8800-0010    | Red Trans., +10 to +32VDC, Analog input, Prescale                     | X                        |                    | X            |               |                      |
| 8810-0010    | Reflective, +10 to +32VDC, Analog input, Prescale                     |                          | X                  | X            |               |                      |
| 8800-0001    | Red Trans., +10 to +32VDC, Analog output, Prescale                    | X                        |                    |              | X             |                      |
| 8810-0001    | Reflective, +10 to +32VDC, Analog output, Prescale                    |                          | X                  |              | X             |                      |
| 8800-0110    | Red Trans., +10 to +32VDC, Analog input, Prescale, RS485              | X                        |                    | X            |               | X                    |
| 8810-0110    | Reflective, +10 to +32VDC, Analog input, Prescale, RS485              |                          | X                  | X            |               | X                    |
| 8800-0101    | Red Trans., +10 to +32VDC, Analog output, Prescale,RS485              | X                        |                    |              | X             | X                    |
| 8810-0101    | Reflective, +10 to +32VDC, Analog output, Prescale,RS485              |                          | X                  |              | X             | X                    |
| 8800-0011    | Red Trans., +10 to +32VDC, Analog input & output, Prescale            | X                        |                    | X            | X             |                      |
| 8810-0011    | Reflective, +10 to +32VDC, Analog input & output, Prescale            |                          | X                  | X            | X             |                      |
| 8800-0111    | Red Trans, + 10VDC to +32VDC, Analog input & output, Prescale, RS485  | X                        |                    | X            | X             | X                    |
| 8810-0111    | Reflective, + 10VDC to +32VDC, Analog input & output, Prescale, RS485 |                          | X                  | X            | X             | X                    |

## ACCESSORIES

200557-001S Relay module 2 form C relays  
 200557-002S AC Voltage module, +90VAC to +250VAC also outputs +12VDC for base unit & sensor