


Universal Phase Monitor C/W Rapid Cycle Lockout


ORDERING INFORMATION

MODEL NUMBER	DESCRIPTION
SLU-0200	Voltage/Phase Monitor

TOP LABEL



DIMENSIONS (INCHES)



SLU-0200 Phase Monitor Relays (3-Phase Monitors) provide cost-effective protection against premature equipment failure caused by voltage faults on 3-Phase systems (Wye or Delta). The SLU-0200 Series multi-mode phase monitoring relay, was designed for the convenience of electrician's, maintenance managers and engineers. This device can be easily adjusted for the voltage, imbalance percentage and time delay requirements to protect against unbalanced voltages or single phasing regardless of any regenerative voltages.

Both **DELTA** and **WYE** systems may be monitored. In Wye systems, connections to neutral are NOT required. The SLU-0200 Series is UL Listed under UL File Number E55826.

NOTE: Can be used for most generator applications. Not recommended for variable frequency drive applications. Call technical support for application assistance.

SPECIFICATIONS

AUTO	Frequency	Nominal Line-to-Line	Adjustable		
RANGING		Voltages	Range		
SCALES	60Hz	208, 220, 240, 380,	200-250		
		415, 440, 460, 480	360-500		
	50Hz	208, 220, 240	200-250		
		346, 380, 415	330-430		
VOLTAGE BAND	Drop-out	±10% of Range Settir	ng (Under/Over)		
	Pick-up	±7% of Range Setting			
MAXIMUM VOLTAGE	550 VAC (Line-to-Line)				
PHASE	ABC (Will Not Operate On CBA Sequence)				
SEQUENCE					
POWER REQUIRED	90VA Max.				
PHASE	2% to 10%, Adjustable Drop-out				
UNBALANCE	Hysteresis 10% of Setting				
PHASE SHIFT	13° Drop-out, 12° Pick-up (Ø-Loss)				
FREQUENCY SHIFT	Not Detected				
RAPID CYCLE	5 Cycle Lockout, 30 minute cycle count reset				
	Automatic				
RESET	Automatic				
RESET RELAY OUTPUT		240VAC Resistive, 1/2 H	P @240VAC		
		9 240VAC Resistive, 1/2 H Flashing	P @240VAC Continuous		
RELAY OUTPUT					
RELAY OUTPUT	SPDT, 10A @	Flashing	Continuous		
RELAY OUTPUT	SPDT, 10A @	Flashing	Continuous Relay Energized Relay		
RELAY OUTPUT	SPDT, 10A @ Normal (Green LED)	Flashing Fault Delay Active	Continuous Relay Energized		
RELAY OUTPUT	SPDT, 10A @ Normal (Green LED) Fault	Flashing Fault Delay Active	Continuous Relay Energized Relay		
RELAY OUTPUT INDICATORS	SPDT, 10A @ Normal (Green LED) Fault (Red LED)	Flashing Fault Delay Active Restart Delay Active	Continuous Relay Energized Relay De-energized		
RELAY OUTPUT INDICATORS	SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U	Continuous Relay Energized Relay De-energized		
RELAY OUTPUT INDICATORS	SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal)	Continuous Relay Energized Relay De-energized Ile nbalance or		
RELAY OUTPUT INDICATORS	SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U	Continuous Relay Energized Relay De-energized Ile nbalance or		
RELAY OUTPUT INDICATORS	SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal) 0.5 to 300 S, Adjustab 32° to 131°F (0° to +	Continuous Relay Energized Relay De-energized Ide Inbalance or Ide (Auto Reset) -55°C)		
RELAY OUTPUT INDICATORS RESPONSE	SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal) 0.5 to 300 S, Adjustab	Continuous Relay Energized Relay De-energized Ide Inbalance or Ide (Auto Reset) -55°C)		
RELAY OUTPUT INDICATORS RESPONSE TEMPERATURE	SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart Operate	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal) 0.5 to 300 S, Adjustab 32° to 131°F (0° to + -49° to 185°F (-45° t	Continuous Relay Energized Relay De-energized Ide Inbalance or Ide (Auto Reset) -55°C)		
RELAY OUTPUT INDICATORS RESPONSE TEMPERATURE RATINGS	SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart Operate Storage	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal) 0.5 to 300 S, Adjustab 32° to 131°F (0° to + -49° to 185°F (-45° t	Continuous Relay Energized Relay De-energized Ide nbalance or Ide (Auto Reset) -55°C) o +85°C)		
RELAY OUTPUT INDICATORS RESPONSE TEMPERATURE RATINGS REPEAT ACCURACY	SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart Operate Storage 1% @ Fixed	Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal) 0.5 to 300 S, Adjustab 32° to 131°F (0° to + -49° to 185°F (-45° t Condition 8-Pin Plug In LEXAN®	Continuous Relay Energized Relay De-energized Ide nbalance or Ide (Auto Reset) -55°C) o +85°C)		