

Specified for use with all Storm AXS access control systems this touch-less technology exit switch allows personnel to leave a secured area by simply waving their hand across an illuminated sensor.

### Installation

- Fits into a standard USA single gang wall box (box not included)
- Supplied with fixing screws for the wall box
- Make the electrical connections using a connector block
- Secure the case to the wall box (cross head screwdriver)
- Test :-

- When the unit is powered the sensor ring is blue
- When your hand is in front of the sensor it changes colour to red and switches the relay

Wiring Connections	
Connection to supply	
Red	+12 Volts
Black	0 Volts
Connection to strike / mag lock	
Green	Normally Closed
White	Common
Yellow	Normally Open



### DEEX010 Request to Exit Switch

Rating 12V DC ,50mA (max)  
 Relay 30V DC , 3A (max)  
 Status LED Blue (powered) / Red (open)  
 Operational Temp 0°C to 50°C

Approvals CE FCC  
 Packed Size 130 x 90 x 50mm, 120g

### Order Codes for AXS Accessories

#### MAG LOCKS

DEL600  
 DEL1200  
 DEGL1200

Door Lock 600 lbs with brackets  
 Door Lock 1200 lbs with brackets  
 Gate Lock 1200 lbs with brackets

#### PSU

DEPSU03

Power Supply in Wall Box, 120V, 6A/12V o/p

#### SWITCHES

DEEX010  
 DEEM010

Request to Exit Switch (IR)  
 Emergency Override Switch with Siren

Document Ref :

**DE-EX01-08KT**  
 Rev 1 July 2014

Whilst every effort is made to ensure details are correct at time of print, specifications are subject to change without notice

Storm Interface products include technology protected by international patents and design registration. All rights reserved.

Storm is a trademark of Keymat Technology Ltd  
 Storm Interface is a trading name of Keymat Technology Ltd

For more information and to order  
[www.storm-interface.com](http://www.storm-interface.com)

