Product data sheet Characteristics

ATV12H037M2

variable speed drive, Altivar 12, 0.37kW, 0.55hp, 200 to 240V, 1 phase, with heat sink





Main

Range of Product	Altivar 12
Product or Component Type	Variable speed drive
Product Specific Application	Simple machine
Mounting Mode	Cabinet mount
Communication Port Protocol	Modbus
Supply frequency	50/60 Hz +/- 5 %
[Us] rated supply voltage	200240 V - 1510 %
Nominal output current	2.4 A
Maximum Horse Power Rating	0.55 hp
Motor power kW	0.37 kW
Maximum Horse Power Rating	0.55 hp
EMC filter	Integrated
IP degree of protection	IP20

Complementary

4
2
1
1
1
2-wire RS 485
1 RJ45
2.4 A 4 kHz
Server Modbus serial
0.5400 Hz
120
20 Ms +/- 1 ms logic input 10 ms analogue input
+/- 0.3 % of maximum value analogue input
Analog input converter A/D, 10 bits Display unit 0.1 Hz
20 ms +/- 1 ms for reference change
9.6 kbit/s 19.2 kbit/s 38.4 kbit/s
RTU
1247
8 bits, configurable odd, even or no parity
Read holding registers (03) 29 words Write single register (06) 29 words Write multiple registers (16) 27 words Read/Write multiple registers (23) 4/4 words Read device identification (43)
No impedance

and/or technical characteristics of the performance of the products contained herein.

determining usitiability or fallshilly of these products for specific user applications.
plete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof, a shall be responsible or liable for misuse of the information contained herein.

Asynchronous motor control profile Sensorless flux vector control Voltage/Frequency ratio (V/f) Quadratic voltage/frequency ratio Maximum output frequency 4 kHz Transient overtorque 150170 % of nominal motor torque depending on drive rating and type of motor Acceleration and deceleration ramps Linear from 0 to 999.9 s S U Motor slip compensation Adjustable Preset in factory Switching frequency 216 kHz adjustable 416 kHz with derating factor Nominal switching frequency 4 kHz Braking to standstill By DC injection Brake chopper integrated False Line current 5.9 A 100 V heavy duty) 4.9 A 120 V heavy duty) Maximum Input Current per Phase 4.9 A Maximum output voltage 240 V
Transient overtorque 150170 % of nominal motor torque depending on drive rating and type of motor Acceleration and deceleration ramps Linear from 0 to 999.9 s S U Motor slip compensation Adjustable Preset in factory Switching frequency 216 kHz adjustable 416 kHz with derating factor Nominal switching frequency 4 kHz Braking to standstill By DC injection Brake chopper integrated False Line current 5.9 A 100 V heavy duty) 4.9 A 120 V heavy duty) Maximum Input Current per Phase 4.9 A Maximum output voltage 240 V
Acceleration and deceleration ramps Linear from 0 to 999,9 s S U Motor slip compensation Adjustable Preset in factory Switching frequency 216 kHz adjustable 416 kHz with derating factor Nominal switching frequency 4 kHz Braking to standstill By DC injection Brake chopper integrated False Line current 5.9 A 100 V heavy duty) 4.9 A 120 V heavy duty) Maximum Input Current per Phase 4.9 A Maximum output voltage 240 V
S U Motor slip compensation Adjustable Preset in factory Switching frequency 216 kHz adjustable 416 kHz with derating factor Nominal switching frequency 4 kHz Braking to standstill By DC injection Brake chopper integrated False Line current 5.9 A 100 V heavy duty) 4.9 A 120 V heavy duty) Maximum Input Current per Phase 4.9 A Maximum output voltage 240 V
Motor slip compensation Adjustable Preset in factory Switching frequency 216 kHz adjustable 416 kHz with derating factor Nominal switching frequency 4 kHz Braking to standstill By DC injection Brake chopper integrated False Line current 5.9 A 100 V heavy duty) 4.9 A 120 V heavy duty) Maximum Input Current per Phase 4.9 A Maximum output voltage 240 V
416 kHz with derating factor Nominal switching frequency 4 kHz Braking to standstill By DC injection Brake chopper integrated False Line current 5.9 A 100 V heavy duty) 4.9 A 120 V heavy duty) Maximum Input Current per Phase 4.9 A Maximum output voltage 240 V
Braking to standstill Brake chopper integrated False Line current 5.9 A 100 V heavy duty) 4.9 A 120 V heavy duty) Maximum Input Current per Phase 4.9 A Maximum output voltage 240 V
Brake chopper integrated False Line current 5.9 A 100 V heavy duty) 4.9 A 120 V heavy duty) Maximum Input Current per Phase 4.9 A Maximum output voltage 240 V
Line current 5.9 A 100 V heavy duty) 4.9 A 120 V heavy duty) Maximum Input Current per Phase 4.9 A Maximum output voltage 240 V
4.9 A 120 V heavy duty) Maximum Input Current per Phase 4.9 A Maximum output voltage 240 V
Maximum output voltage 240 V
Apparent power 1.2 kVA 240 V heavy duty)
Maximum transient current 3.6 A 60 s heavy duty) 4.0 A 2 s heavy duty)
Network Frequency 50-60 Hz
Relative symmetric network frequency tolerance 5 %
Prospective line Isc 1 kA
Base load current at high overload 2.4 A
Power dissipation in W Natural 27.0 W
With safety function Safely Limited Speed (SLS) False
With safety function Safe brake management (SBC/ False SBT)
With safety function Safe Operating Stop (SOS) False
With safety function Safe Position (SP) False
With safety function Safe programmable logic False
With safety function Safe Speed Monitor (SSM) False
With safety function Safe Stop 1 (SS1) False
With sft fct Safe Stop 2 (SS2) False
With safety function Safe torque off (STO) False
With safety function Safely Limited Position (SLP) False
With safety function Safe Direction (SDI) False
Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t
Tightening torque 7.08 lbf.in (0.8 N.m)
Insulation Electrical between power and control
Quantity per Set Set of 1
Width 2.83 in (72 mm)
Height 5.63 in (143 mm)
Depth 4.77 in (121.2 mm)
Product Weight 1.54 lb(US) (0.7 kg)

Environment

> 3280.846561.68 ft (> 10002000 m) with current derating 1 % per 100 m <= 3280.84 ft (1000 m) without derating	
Vertical +/- 10 degree	
NOM CSA C-tick UL GOST RCM KC	
CE	
UL 508C UL 618000-5-1 EN/IEC 61800-5-1 EN/IEC 61800-3	
With heat sink	
Electrical fast transient/burst immunity test level 4 EN/IEC 61000-4-4 Electrostatic discharge immunity test level 3 EN/IEC 61000-4-2 Immunity to conducted disturbances level 3 EN/IEC 61000-4-6 Radiated radio-frequency electromagnetic field immunity test level 3 EN/IEC 61000-4-3 Surge immunity test level 3 EN/IEC 61000-4-5 Voltage dips and interruptions immunity test EN/IEC 61000-4-11	
Class 3C3 according to IEC 60721-3-3 Class 3S2 according to IEC 60721-3-3	
150 m/s² at 11 ms	
10 m/s² at 13200 Hz	
1.5 mm at 213 Hz	
Class III	
Adjustable PID regulator	
Radiated emissions environment 1 category C2 EN/IEC 61800-3 216 kHz shielded motor cable Conducted emissions with integrated EMC filter environment 1 category C1 EN/IEC 61800-3 2, 4, 8, 12 and 16 kHz shielded motor cable <16.40 ft (5 m) Conducted emissions with integrated EMC filter environment 1 category C2 EN/IEC 61800-3 212 kHz shielded motor cable <16.40 ft (5 m) Conducted emissions with integrated EMC filter environment 1 category C2 EN/IEC 61800-3 2, 4 and 16 kHz shielded motor cable <32.81 ft (10 m) Conducted emissions with additional EMC filter environment 1 category C1 EN/IEC 61800-3 412 kHz shielded motor cable <65.62 ft (20 m) Conducted emissions with additional EMC filter environment 1 category C2 EN/IEC 61800-3 412 kHz shielded motor cable <164.04 ft (50 m) Conducted emissions with additional EMC filter environment 2 category C3 EN/IEC 61800-3 412 kHz shielded motor cable <164.04 ft (50 m)	
1 gn 13200 Hz)EN/IEC 60068-2-6 1.5 mm peak to peak 313 Hz) - drive unmounted on symmetrical DIN rail - EN/ IEC 60068-2-6	
15 gn 11 ms EN/IEC 60068-2-27	
595 % without condensation IEC 60068-2-3 595 % without dripping water IEC 60068-2-3	
0 dB	
2	
-13158 °F (-2570 °C)	
14…104 °F (-10…40 °C) without derating 104…140 °F (40…60 °C) with current derating 2.2 % per °C	
-13158 °F (-2570 °C)	

Category	22042-ATV12 DRIVE AND ACCESSORIES
Discount Schedule	CP4B
GTIN	3606480071058
Returnability	Yes
Country of origin	ID

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.96 in (12.600 cm)
Package 1 Width	7.87 in (20.000 cm)
Package 1 Length	7.36 in (18.700 cm)
Package 1 Weight	2.28 lb(US) (1.035 kg)
Unit Type of Package 2	P06
Number of Units in Package 2	45
Package 2 Height	29.53 in (75.000 cm)
Package 2 Width	23.62 in (60.000 cm)
Package 2 Length	31.50 in (80,000 cm)
Package 2 Weight	131,24 lb(US) (59,530 kg)

Offer Sustainability

Sustainable offer status	Green Premium product
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov
REACh Regulation	REACh Declaration
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) EEU RoHS Declaration
Mercury free	Yes
China RoHS Regulation	☑ China RoHS Declaration
RoHS exemption information	₫Yes
Circularity Profile	End Of Life Information
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.


Contractual warranty

Contracted warranty	
Warranty	18 months

ATV12H037M2

Dimensions

Drive without EMC Conformity Kit




Dimensions in mm

b	С	Н
130	121.2	120

Dimensions in in.

b	С	Н
5.12	4.77	4.72

Drive with EMC Conformity Kit



Dimensions in mm

c1	
53	

Dimensions in in.


c1	
2.09	

Product data sheet Mounting and Clearance


ATV12H037M2

Mounting Recommendations


Clearance for Vertical Mounting



Mounting Type A




Mounting Type B




Remove the protective cover from the top of the drive.

Mounting Type C



Remove the protective cover from the top of the drive.


Single-Phase Power Supply Wiring Diagram



- A1 Drive
- KM1 Contactor (only if a control circuit is needed)
- P1 2.2 k Ω reference potentiometer. This can be replaced by a 10 k Ω potentiometer (maximum).
- Q1 Circuit breaker
- (1) Negative logic (Sink)
- (2) Positive logic (Source) (factory set configuration)
- (3) 0...10 V or 0...20 mA

Recommended Schemes

2-Wire Control for Logic I/O with Internal Power Supply




LI1 : Forward LI• : Reverse A1 : Drive

3-Wire Control for Logic I/O with Internal Power Supply




LI1: Stop LI2: Forward LI•: Reverse A1: Drive

Analog Input Configured for Voltage with Internal Power Supply



(1) 2.2 k Ω ...10 k Ω reference potentiometer A1 : Drive


Analog Input Configured for Current with Internal Power Supply



0-20 mA 4-20 mA supply

À1: Drive


Connected as Positive Logic (Source) with External 24 vdc Supply



(1) 24 vdc supply

A1: Drive

Connected as Negative Logic (Sink) with External 24 vdc supply




24 vdc supply (1)

A1: Drive

Product data sheet Performance Curves

ATV12H037M2

Torque Curves



- 1: Self-cooled motor: continuous useful torque (1)
- 2: Force-cooled motor: continuous useful torque
- 3: Transient overtorque for 60 s
- 4: Transient overtorque for 2 s
- 5: Torque in overspeed at constant power (2)
- (1) For power ratings ≤ 250 W, derating is 20% instead of 50% at very low frequencies.
- (2) The nominal motor frequency and the maximum output frequency can be adjusted from 0.5 to 400 Hz. The mechanical overspeed capability of the selected motor must be checked with the manufacturer.