

Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com

# DataShield In-Line Surge Protector for Network and Phone Lines, 1-Line RJ45

## MODEL NUMBER: DNET1



#### Description

Tripp Lite's DNET1 provides network Ethernet line surge suppression for 100Base-T, 10Base-T, Token Ring, AS400/Sys3x and RS422 applications. Surge suppression is handled with balanced arrays of highspeed avalanche diodes that divert excess energies created by electrostatic discharges, faulty wiring or lightning away from network interface connections. Tripp Lite network surge suppressors reduce blown NIC cards, garbled network transmissions, system lock-ups and hard equipment failure by safely shunting dataline surges to ground. Convenient RJ45 input and output connections with an included 5-inch Ethernet patch cable enables ideal protection for network workstations, printers and other internetworking devices with a network connection. For peace of mind, the DNET1 comes with a lifetime warranty and RoHS-compliant design.

#### Features

- DNET1 protects network workstations, printers and internetworking devices from surges present on 10/100Base-T, token ring, AS400/Sys3x or RS422 network lines
- Convenient RJ45 input and output connections make for simple installation (RJ45 input/output connections, pins 1-8, 7.5V clamping)
- 5 inch Ethernet patch cable enables ideal protection placed as close as possible to the point of use
- Surge suppression utilizing high speed avalanche diodes divert excess energies on the network to ground
- RoHS Compliance
- Lifetime Warranty

# **Specifications**

### Highlights

- Network Ethernet line surge suppression for 100Base-T, 10Base-T, Token Ring, AS400/Sys3x and RS422 applications
- Ideal protection for NICs, terminals, hubs, printers, LAN equipment, and other internetworking devices
- Protects against the effects of electrostatic discharge, faulty wiring and lightning
- Reduces blown NIC cards, garbled network transmissions, system lock-ups and hard equipment failure
- 750A circuit breaker; 7.5V nominal clamping voltage
- RJ45 input and output connections with included patch cable

#### **Package Includes**

- DNET1 dataline protector
- 5-in. RJ45 patch cable
- Warranty information and instruction manual



| MODEL TEXT                             |   |
|--|---|
| Key Benefit                            | Protects network<br>datalines on workstations, printers, hubs and other devices from blown NIC<br>cards, garbled transmissions, lock-ups and hardware failures caused by surges,<br>line noise, ESD, faulty wiring and lightning. |
| ουτρυτ                                 |   |
| Output Receptacles                     | (1) Network   |
| Circuit Breaker (amps)                 | 750   |
| INPUT                                  |   |
| Nominal Input Voltage(s) Supported     | 120V AC; 230V AC  |
| Recommended Electrical Service         | 120V, 230V  |
| Input Connection Type                  | RJ45  |
| Input Cord Length (ft.)                | 0   |
| Input Cord Length (m)                  | 0.00  |
| Right-Angle Plug                       | 0   |
| SURGE / NOISE SUPPRESSION              |   |
| AC Suppression Joule Rating            | 0   |
| Clamping Voltage (RMS)                 | 7.5   |
| DATALINE SURGE SUPPRESSION             |   |
| Telephone/DSL Protection               | 1   |
| Telephone/DSL Protection Details       | 1 line  |
| Cable (Coax) Protection                | 0   |
| Network (Ethernet) Protection          | 1   |
| Additional Dataline Protection         | 1-8   |
| WARRANTY                               |   |
| Product Warranty Period<br>(Worldwide) | Lifetime limited warranty   |

© 2017 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies