Wattstopper's CX-100 Series Passive Infrared (PIR) Ceiling/Wall Sensors detect occupancy to control lighting in a wide variety of applications.

Features & Benefits

Staged:LRProductCatalog		ASIC technology reduces components and provides greater reliability			
Choice of four coverage patterns		Built-in light level sensor			
Isolated relay for use v	with HVAC or other control systems	Automa	tic or manual-on operation when	used with a BZ-150 Power Pack	
Turns lights on and off based on occupancy			User-adjustable time delay and sensitivity		
Specifications					
General Info					
Product Line	Pass & Seymour		Replaced by Part Number	CX-105	
UPC Number	754182911394		Country Of Origin	China	
Features	Motion Sensor, IR (Infrared), Indic Lights	cator	Switch Type	Motion Sensor	
Application Sector	Commercial		Warranty Type	5-Year	
Dimensions					
Product Width US	3.367 in		Product Depth US	2.034 in	
Product Length US	3.335 in				
Technical Informati	on				
Response Frequency	60 Hz		Sensor Type	Occupancy	
Amperage	8 mA		Indicator	LED Light	
Indoor/Outdoor	Indoor		Sensing Range	Up to 2000 sq. ft.	
Voltage	24 V, 24 V		Connection Type	Wired	