### 2 D Mine Safety Light

#### **EXPLOSION-PROOF**

 Will not cause an explosion in certain ignitable gas-air and dust-air atmospheres\*



#### **IMPACT RESISTANT**

 Heavy duty construction minimizes potential for damage to light



#### **NON-CONDUCTIVE**

 Protects user from immediate electricl shock

#### **IDENTIFIABLE**

Internationally known color for instant recognition

## in end cap

#### **HANDY**

 Hanger ring in end cap gives ability to hang up or belt-carry



MSHA approved for use in methane-air mixture and UL listed for Division I and II, Class I, Group C and D environments. \*For use in gas-air mixtures of Acetone, Butane, Benzene, Diethyl Ether, Ethyl and methyl Alcohols, Gasoline, Methane (natural gas), Naphtha and Propane. Approved also for use in dust-air mixtures of Class II, Group G. Designed so that if lamp is broken, electrical circuit will be opened before filament can ignite these flammable or explosive gas-air mixtures in the surrounding atmosphere.

#### **Product Detail:**

**Designation**: Industrial

2 D Mine Safety Light UL/MSHA/CSA approved

Model: 1259

Color: Safety Orange

Power Source: Two "D"
ANSI/NEDA: 15 Series


Lamp: PR-2
Lamp Rating: 2.4V, 0.5A
Lamp Life: 15 Hours
Lamp Output: 11.4 Lumens
Typical Weight: 113 grams (4.0 oz.)

(without batteries)

**Dimensions (in):** 2.37 x 2.37 x 8

#### Performance:

#### **Run Time**



# 2.37 in.

#### WARNING:

USE ONLY PR-2 AND 2 SIZE "D"
1.5 VOLT ALKALINE BATTERIES.
RISK OF EXPLOSION – DO NOT OPEN IN HAZARDOUS
AREA. TO PREVENT THE IGNITION OF A HAZARDOUS
ATMOSPHERE, BATTERIES MUST ONLY BE CHANGED IN
AN AREA KNOW TO BE NON-HAZARDOUS.

#### **Before Using Your Flashlight:**

Please read all instructions and cautionary markings on the package and light

#### **Important Notice**

This datasheet contains information specific to products manufactured at the time of its publication

Contents herein do not constitute a warranty ©Energizer / All Rights Reserved

