UK universal modular terminal blocks, SK shield connection clamps

UK universal terminal blocks

Connectors for all disconnect terminal blocks in the UK series

- The ST-SI-UK 4 fuse connector for 5 x 20 mm cartridge fuse inserts is available with and without a LED
- The ST-BE component connector is available as an individual connector for two-pos. components and as a double connector

- $^{\mbox{\tiny 1}})$ If the fuse is faulty, the downstream circuit is not off load.
- ²) Integrated: Diode 1N 4007, reverse voltage: 1300 V, maximum continuous current: 1.0 A
- 3) With single arrangement.
- 4) Integrated: B 250 C 1500 rectifier, reverse voltage: 600 V, nominal voltage: 250 V, nominal current: 1.5 A



Fuse connector for 5 x 20 mm cartridge fuses



Component connector for 2- and 4-pos. components





Rated data	
Rated voltage	[V]
Nominal current/cross section	[A]/[mm²]
Rated cross section	[mm ²]
Cross-section range	AWG
General data	
Tightening torque	[Nm]
Insulating material	
Inflammability class according to UL 94	

Technical data							
IEC	UL/CUL	CSA	IEC/ EN 60079-7				
250	300	300	-				
6.3/-	6.3/-	10/-	-				
-	-	-	-				
-	-	-	-				
-							
PA							
V2							

Technical data						
IEC	UL/CUL	CSA	IEC/ EN 60079-7			
-	300	-	-			
16/-	10/-	-	-			
-	-	-	-			
-	30-14	-	-			
0.5 - 0.6 PA V2						

		Ordering data		Ordering data			
Description	Color	Туре	Order No.	Pcs./ Pkt.	Туре	Order No.	Pcs./ Pkt.
Fuse connector for cartridge fuse inserts 5 x 20 mm, 26.5 mm high, max. 6.3 A	black	ST-SI-UK 4	0921011	50			
Fuse connector, for cartridge fuse inserts, 5 x 20 mm, 26.5 mm high, max. 6.3 A, with LED, for 5 - 15 V AC/DC¹)	black	ST-SILED 12-UK 4	0921024	50			
With LED for 15 - 30 V AC/DC With LED for 30 - 60 V AC/DC With LED for 110 - 250 V AC/DC	black black black	ST-SILED 24-UK 4 ST-SILED 60-UK 4 ST-SILA250-UK 4	0921037 0921040 0921053	50 50 50			
Component connector, for switching on 2-pos. components in the basic terminal block, fixing at screw terminal points, 19 mm high, max. 16 A³)	gray				ST-BE	2802316	10
Component connector, to connect 2-pos. components into the basic terminal block, 19 mm high, with LED for 24 V AC/DC					ST-BE-LA 24	2802374	10
With LED for 230 V AC/DC					ST-BE-LA230	2802387	10
Component connector, to connect 2-pos. components into the basic terminal block, with diode 1N 4007, 19 mm high²)					ST-1N4007	2802329	10
Component connector, for 4-pos. components, two basic terminal blocks required per connector, 19 mm high	gray				ST-BE-VP	2802332	10
Component connector, for 4-pos. components, two basic terminal blocks required per connector, with bridge rectifier B 250 C 1500, 19 mm high4)					ST-B250C1500	2802345	10
Isolating connector, 13.5 mm high, max. 16 A					ST-K 4	5025462	50
		Accessories		Accessories			
Plug pliers, simplify the removal of the isolating connector from a closed row of terminal blocks					тz	0306704	10
Center groove labeling					ZB 6 (CLIPLINE catalog, part 2)		