# **Online Pro**

**Orion Power Systems** 

True Online Power Protection from 1000VA to 3000VA



**Orion Power Systems Online Pro** Series provides the ultimate in power quality, manageability, and flexibility.

## Ideally suited for:

- Medical and lab equipment
- Data processing
- Network closets
- **VOIP** and Telecom

# **Product Snapshot**

**Power Rating** 

1000VA/800W 1500VA/1050W 2000VA/1600W 3000VA/2400W

Input Voltage Range **Output Voltage Range** Frequency (HZ) Topology Configuration

60/70/80 - 144Vac 115V, adjustable to 100/110/115/120/127 50/60 +/- 5Hz (Auto Sensing) True On-line Double Conversion Rack (2U) / Tower – pedestal and rack mount kit included


#### **Features**

- Protect valuable equipment with tight voltage regulation and pure sine wave output.
- Conserve valuable rack space with 2U rack height
- Flexible form factor allows rack mounted or tower deployment
- Stay informed with Free monitoring software or optional SNMP management
- Extended backup time available with add-on battery modules
- Rotating LCD display provides instant information and control of **UPS**
- 2 Year warranty coverage on electronics and batteries



# **Ultimate Power Quality**

Ensure your sensitive equipment lasts longer and is more reliable by supplying it with quality power. The Online Pro series uses double conversion technology to regulate voltage +/- 1% and outputs a pure sine wave. During a power outage, there is no transfer time when going to battery power.



### Communications

Online Pro keeps you in the know with Free monitoring and shutdown software operated via USB or DB9 serial port. Optional communication cards provide Web/SNMP and relay contact communication.



# **LCD Display**

State of the Art LCD display rotates to accommodate tower or rack mount installations. Provides real time status information and allows configuration of ups setup parameters. LCD display reports Volts in, Volts out, battery voltage, percentage load, and more.



# **Hot Swappable Batteries**

Maintenance is easy and inexpensive with user replaceable, hot-swappable battery trays. Save money on maintenance by using inhouse personnel to change batteries when necessary.



# Online Pro Adapts to Your Needs

- Tower or Rack-mount installation
- Add backup time when needed with extended battery modules
- Load shedding allows shutdown of non-critical equipment in prolonged outages
- Adjustable output voltage to 100/110/115/120/127
- Frequency converter from 50 to 60HZ or vice versa

#### **Battery Backup time in Minutes \***

| Load (VA/Watts) | Internal<br>Batteries | 1 EBM | 2 EBM | 3 EBM | 4 EBM |
|-----------------|-----------------------|-------|-------|-------|-------|
| DC1000U         |                       |       |       |       |       |
| 500/350         | 19                    | 158   | 326   | 508   | 699   |
| 1000/700        | 7                     | 66    | 139   | 219   | 304   |
| DC1500U         |                       |       |       |       |       |
| 750/525         | 15                    | 131   | 270   | 422   | 582   |
| 1500/1050       | 6                     | 54    | 114   | 181   | 252   |
| DC2000U         |                       |       |       |       |       |
| 1000/700        | 19                    | 83    | 158   | 240   | 326   |
| 2000/1400       | 7                     | 33    | 66    | 101   | 139   |
| DC3000U         |                       |       |       |       |       |
| 1500/1050       | 15                    | 68    | 131   | 198   | 270   |
| 3000/2100       | 6                     | 27    | 54    | 83    | 114   |

<sup>\*</sup> Runtimes are approximate and will vary based on battery age, temperature, etc.

#### **Model Selection Guide**

| Online Pro Rack/Tower Models: 120V 50/60HZ |                       |        |                     |                    |               |  |  |  |  |
|--|-----------------------|--------|---------------------|--------------------|---------------|--|--|--|--|
| Model #                                    | Rating (VA/Watts)     | Input  | Output Receptacles  | Dim. HxWxD (in.)   | Weight (lbs.) |  |  |  |  |
| DC1000U                                    | 1000/800              | 5-15P  | (6) 5-15R           | 3.5 (2U) x 18 x 16 | 34.5          |  |  |  |  |
| DC1500U                                    | 1500/1050             | 5-15P  | (6) 5-15R           | 3.5 (2U) x 18 x 16 | 34.5          |  |  |  |  |
| DC2000U                                    | 2000/1600             | 5-20P  | (2) 5-15R (2) 5-20R | 3.5 (2U) x 18 x 26 | 61.3          |  |  |  |  |
| DC3000U                                    | 3000/2400             | L5-30P | (4)5-15R (1) L5-30R | 3.5 (2U) x 18 x 26 | 68.6          |  |  |  |  |
| Rack/Towe                                  | r Extended Battery Me | odules |                     |                    |               |  |  |  |  |
| DC1500EBM                                  | For 1000/1500 VA      | N/A    | N/A                 | 3.5 (2U) x 18 x 16 | 92            |  |  |  |  |
| DC2000EBM                                  | For 2000/3000 VA      | N/A    | N/A                 | 3.5 (2U) x 18 x 26 | 76            |  |  |  |  |
| OPS-Railkit                                | N/A                   | N/A    | N/A                 | N/A                | 3             |  |  |  |  |

# Specifications:

**Electrical Input** 

Nominal Voltage 115V

**Voltage Range** 60/70/80\* – 144 VAC **Frequency (HZ)** 50/60 +/- 5Hz (Auto Sensing)

Power Factor > .99 (Full Load)

\* Based on load percentage (0~33/33~66/66~100%)

**Electrical Output** 

Output Voltage 115V, adjustable to 100/110/115/120/127

Voltage Regulation ≤± 1%

**Frequency (HZ)** ±0.1% (0.05~0.06Hz) unless

synchronized to line > .99 (Full Load)

Power Factor > .99 (Full Load)
Load Segments Two user controlled load

segments

Wave Form True Sine Wave

**Warranty and Protection** 

Warranty 2 year warranty on electronics and

batteries.

Load Protection \$ 150,000 (U.S. only)

Guarantee

#### Communications

Interface Type SNMP(optional)

Monitoring / Shutdown Software

1 \*USB port+ 1\*RS-232 port Power management from SNMP manager and Web browser Windows 95/98/NT/2000/XP /Vista/7 Novell NetWare, Linux, etc. Included at no charge.

## **Environmental**

Operation Temperature 0-40 C Noise Level <50dBA

Relative Humidity 0 to 90% (without condensation)

### **Standards and Certification**

Safety IEC/EN 62040-1-1,IEC 60950-1

Performance IEC/EN 62040-3

IEC/EN62040-2 Class A, FCC Part 15 Subpart B
EMC Class A, IEC/EN55011, CISPR11, IEC61000-4-2/-

3/-4/-5, IEC61000-2-2, IEC61000-3-2/-3

Markings UL 1778, FCC



Orion Power Systems, Inc.

8640 Philips Hwy Bldg 2 Suite 20 Jacksonville, FL 32256

877.385.1654

www.orionpowersystems.com