

SmartPro 230V 1.5kVA 940W Line-Interactive UPS, Tower, DB9, 6 Outlets

MODEL NUMBER: SMARTINT1500





Description

The SMARTINT1500 SmartPro 230V 1.5kVA 940W Line-Interactive UPS provides battery backup and AC power protection against blackouts, brownouts, power surges and line noise that can damage electronics or destroy data. Ideal for backing up VoIP systems, point-of-sale applications and network closets, the SMARTINT1500 switches to battery mode in milliseconds to keep your connected equipment running long enough to save files and shut down safely with no data loss.

Featuring six IEC-320-C13 outlets and two C13-to-C14 power cords, the SMARTINT1500 has an internal battery that provides 20 minutes of support at half load and seven minutes at full load. Front-panel LEDs indicate line power, battery power, load level, voltage regulation and battery status. An alarm sounds to indicate power failure or a low battery.

Automatic voltage regulation (AVR) maintains 230V nominal output over an input range of 165V to 277V without using battery power. EMI/RFI noise filtering improves your equipment's performance and prevents damage. A 480-joule surge suppression rating protects your equipment from harmful power surges. With Tripp Lite's PowerAlert software (available via free download), SMARTINT1500 enables safe unattended system shutdown and file saves in case of a prolonged power failure.

Features

Protects Mission-Critical Equipment

- · Provides fully regulated AC output for VoIP systems, point-of-sale applications and network closets
- Audible alarm signals loss of utility power or low battery
- 6 IEC-320-C13 outlets
- C14 inlet
- 480-joule surge suppression rating

Highlights

- Corrects under- and overvoltages from 165V to 277V
- 6 IEC-320-C13 outlets
- Front-panel LEDs indicate load, power and battery statuses
- Monitoring of power conditions via PowerAlert®
- 20 min. runtime at half load; 7 min. at full load

Package Includes

- SMARTINT1500 SmartPro 230V
 1.5kVA 940W Line-Interactive
 UPS
- (2) IEC-320 C13-to-C14 power cables
- (2) <u>DB9</u> cables
- Owner's manual



Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com

Reliable Battery Backup

- Supports half load up to 20 min. and full load up to 7 min.
- Internal batteries designed for hot-swap field replacement
- 94% line-power efficiency rating saves money in energy costs
- · Cold-start capability enables turn-on in battery mode during blackouts

Automatic Voltage Regulation (AVR)

• Maintains 230V nominal output over input range of 165V-277V without using battery power

EMI/RFI Line Noise Filtering

 Removes electromagnetic and radio frequency interference that can disrupt or damage equipment's performance

LED Indicators

• Front-panel LEDs signal indicate line power, battery power, load level, voltage regulation and battery status

Communications Port

• <u>DB9</u> port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from <u>www.tripplite.com/poweralert</u>

Small-Footprint Tower Housing

Mounts on wall with optional <u>UPSWM</u> accessory

Specifications

MODEL TEXT		
Key Benefit	Protects connected mission-critical equipment against damage, downtime and data loss due to blackouts, brownouts, power surges and line noise. Ideal solution for VoIP systems, point-of-sale applications and network closets.	
OUTPUT		
Output Volt Amp Capacity (VA)	1500	
Output kVA Capacity (kVA)	1.5	
Output Watt Capacity (Watts)	940	
Nominal Output Voltage(s) Supported	220V; 230V; 240V	
Nominal Voltage Details	230V nominal output in battery mode	



Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com

Frequency Compatibility	50 / 60 Hz	
Frequency Compatibility Details	Automatic frequency selection	
Output Voltage Regulation (Line Mode)	-15%, +8%	
Output Voltage Regulation (Battery Mode)	+/- 5%	
Output Receptacles	(6) C13	
Included Output Power Cables	Includes 2 C13 to C14 output power cables	
Output AC Waveform (AC Mode)	Sine wave	
Output AC Waveform (Battery Mode)	PWM sine wave	
INPUT		
Rated input current (Maximum Load)	6.5A	
Nominal Input Voltage(s) Supported	230V AC	
UPS Input Connection Type	C14 inlet	
Input Circuit Breakers	10A	
Input Phase	Single-Phase	
BATTERY		
Full Load Runtime (min.)	7 min. (940w)	
Half Load Runtime (min.)	20 min. (470w)	
DC System Voltage (VDC)	36	
Battery Recharge Rate (Included Batteries)	Less than 4 hours from 10% to 90% (typical, full load discharge)	
Internal UPS Replacement Battery Cartridge	RBC53	
Battery Access	Battery access door	
Battery Replacement Description	Hot-swappable, user replaceable batteries	
Expandable Runtime	No	
VOLTAGE REGULATION		
Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 166 to 277	
Overvoltage Correction	Input voltages between 243 and 277 are reduced by 12%	
Undervoltage Correction	Input voltages between 191 and 215 are boosted by 10%	
Severe Undervoltage Correction	Input voltages between 165 and 190 are boosted by 22%	
USER INTERFACE, ALERTS & CONTROLS		



Switches	2 Switches control off/on power status and alarm-cancel/self-test operation
Alarm Cancel Operation	Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low- battery status
Audible Alarm	Audible alarm indicates power-failure and low-battery conditions
LED Indicators	5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status
SURGE / NOISE SUPPRESSION	
UPS AC Suppression Joule Rating	480
UPS AC Suppression Response Time	Instantaneous
EMI / RFI AC Noise Suppression	Yes
PHYSICAL	
Installation Form Factors Supported with Optional Accessories	Wallmount (<u>UPSWM</u> - tower mounting kit)
Primary Form Factor	Tower
UPS Power Module Dimensions (hwd, in.)	12.8 x 7.5 x 9.2
UPS Power Module Dimensions (hwd, cm)	32.51 x 19.05 x 23.37
UPS Power Module Weight (lbs.)	38.6
UPS Power Module Weight (kg)	17.51
UPS Shipping Dimensions (hwd / in.)	18.2 x 12 x 13.8
UPS Shipping Dimensions (hwd / cm)	46.23 x 30.48 x 35.05
Shipping Weight (lbs.)	43.2
Shipping Weight (kg)	19.6
UPS Housing Material	Polycarbonate
Primary UPS Height (mm)	325
Primary UPS Width (mm)	190
Primary UPS Depth (mm)	234
Shipping Height (mm)	462
Shipping Width (mm)	305
Shipping Depth (mm)	351
ENVIRONMENTAL	
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius



[
Relative Humidity	0 to 95%, non-condensing	
AC Mode Efficiency Rating (100% Load)	94%	
COMMUNICATIONS		
Communications Interface	DB9 Serial; Contact closure	
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions; contact closure communications via 2nd DB9 port (2 total)	
PowerAlert Software	For local monitoring via the UPS's built-in DB9 port, download PowerAlert Local software at http://www.tripplite.com/poweralert	
Communications Cable	2 DB9 cables included	
LINE / BATTERY TRANSFER		
Transfer Time	2-4 milliseconds	
Low Voltage Transfer to Battery Power (Setpoint)	165	
High Voltage Transfer to Battery Power (Setpoint)	n/a	
SPECIAL FEATURES		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Hot swappable batteries	
CERTIFICATIONS		
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); CE; Tested to GOST (Russia); Tested to SASO (Saudi Arabia); Tested to IRAM (Argentina)	
UPS Certification Details	EMI approvals 62040	
WARRANTY		
Product Warranty Period (International)	2-year limited warranty	
Product Warranty Period (Mexico)	2-year limited warranty	
Product Warranty Period (Puerto Rico)	2-year limited warranty	

© 2017 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies