

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

DIN Rail-Mounting Bracket for Digital Signage, Version 2 - 65 mm Mounting Distance

MODEL NUMBER: B110-DIN-02











DIN rail bracket securely mounts select Tripp Lite extenders and other digital signage devices to a standard 35 mm DIN rail.

Features

DIN Mounting Bracket Ideal for Attaching Your Digital Signage Components to a DIN Rail

This black aluminum DIN bracket is designed for securely mounting splitters, extenders and other select Tripp Lite digital signage devices to any standard 35 mm DIN rail. Consisting of a durable U bracket and rail clip, the B110-DIN-02 firmly attaches to both lips of the DIN rail to prevent your mounted equipment from being jostled and connected cables from coming loose. It's an ideal accessory for setting up a digital signage system in restaurants, offices, banks, hotels, schools, doctor's offices and a wide range of retail establishments.

Simple Mounting Process Takes Just a Few Minutes

Just use the included screws to attach the aluminum U bracket to the compatible Tripp Lite device. Attach the aluminum rail clip to the bracket, and securely mount the unit on a 35 mm DIN rail, making sure the spring goes over the rail's top lip.

Compatible with a Wide Range of Tripp Lite Digital Signage Devices

This DIN rail-mounting bracket attaches to Tripp Lite units with mounting holes spaced 65 millimeters apart. Select equipment includes the B126-Series, B130-Series, B132-Series and BHDBT-Series of transmitters, receivers and extenders.

Lifetime Warranty

The B110-DIN-02 is backed by a lifetime warranty, ensuring reliability and performance.

Highlights

- Durable U bracket and rail clip mount firmly to any standard 35 mm DIN rail
- Holds Tripp Lite digital signage device securely in place to prevent unwanted movement
- Easy to mount in just a few minutes, so you can get your system up and running quickly
- Fits Tripp Lite digital signage components with mounting holes spaced 65 mm apart
- Includes all necessary mounting hardware for immediate DIN rail installation

Applications

 Mount a Tripp Lite transmitter, receiver or extender to a 35 mm
 DIN rail in a digital signage system

System Requirements

 Select Tripp Lite digital signage device, including B126-, B130-, B132- and BHDBT-Series

Package Includes

- U bracket
- DIN rail clip
- (2) DIN rail screws
- (2) M3 x 5 mm mounting screws
- Installation guide

Specifications

OVERVIEW	
UPC Code	037332213914





Technology	A/V over IP	
PHYSICAL		
Shipping Dimensions (hwd / in.)	4.72 x 3.14 x 0.98	
Shipping Dimensions (hwd / cm)	12.00 x 8.00 x 2.50	
Shipping Weight (lbs.)	0.16	
Shipping Weight (kg)	0.07	
Unit Packaging Type	Вох	
Material of Construction	Aluminum	
Color	Black	
CERTIFICATIONS		
Certifications	RoHS, REACH	
WARRANTY		
Product Warranty Period (Worldwide)	Lifetime limited warranty	

© 2018 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies