SIEMENS

Data sheet

6ES7132-6GD51-0BA0

SIMATIC ET 200SP, Signal relay module, RQ CO 4x 24V DC/2A ST, 4 changeover contacts, isolated contacts, packing unit: 1 piece, fits to BU-type A0, Colour Code CC00, substitute value output, module diagnostics for: supply voltage



Product type designation	RQ CO 4x 24 V DC/2 A ST, PU 1
Firmware version	V0.0
• FW update possible	No
usable BaseUnits	BU type A0
Color code for module-specific color identification	CC00
plate	
Product function	
• I&M data	Yes; I&M0 to I&M3
Engineering with	
 STEP 7 TIA Portal configurable/integrated as of version 	V14
 STEP 7 configurable/integrated as of version 	V5.5 SP3
 PROFIBUS as of GSD version/GSD revision 	One GSD file each, Revision 3 and 5 and higher
 PROFINET as of GSD version/GSD revision 	GSDML V2.3
Operating mode	
• DQ	Yes
 DQ with energy-saving function 	No
• PWM	No

General information

Oversampling	No
• MSO	No
Redundancy	
Redundancy capability	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption (rated value)	50 mA
Power loss	
Power loss Power loss, typ.	1.2 W
Address area	
Address space per module	
Inputs	+ 1 byte for QI information
Outputs	1 byte
Hardware configuration	
Automatic encoding	Yes
 Mechanical coding element 	Yes
Digital outputs Type of digital output	Palava
Number of digital outputs	Relays 4
Current-sinking	Yes
Current-sourcing	Yes
Short-circuit protection	No
Parallel switching of two outputs	
for logic links	Yes
• for uprating	No
 for redundant control of a load 	Yes
Switching frequency	
with resistive load, max.	2 Hz
Total current of the outputs	
Current per channel, max.	2 A
Current per channel, max. Current per module, max.	8 A
Total current of the outputs (per module)	
horizontal installation	
nonzontal installation	
up to 10 °C may	8 /
— up to 40 °C, max.	8 A
— up to 40 °C, max. — up to 50 °C, max. — up to 60 °C, max.	8 A 6 A 4 A

send a shire that the firm	
vertical installation	
— up to 30 °C, max.	8 A
— up to 40 °C, max.	6 A
— up to 50 °C, max.	4 A; in all other mounting positions
Relay outputs	
 Number of relay outputs 	4
 Rated supply voltage of relay coil L+ (DC) 	24 V
 Current consumption of relays (coil current of all relays), max. 	40 mA
Switching capacity of contacts	
— with resistive load, max.	2 A
— Thermal continuous current, max.	2 A
— Switching current, min.	1 mA; 5 V DC
— Rated switching voltage (DC)	24 V
— Rated switching voltage (AC)	24 V
Cable length	
 shielded, max. 	1 000 m
• unshielded, max.	200 m
Isochronous mode	
Isochronous operation (application synchronized up	No
to terminal)	
Interrupts/diagnostics/status information	Yes
Diagnostics function	Yes
Diagnostics function Substitute values connectable	Yes Yes
Diagnostics function Substitute values connectable Alarms	Yes
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm	
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages	Yes
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage	Yes Yes Yes
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break	Yes Yes Yes No
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break • Short-circuit	Yes Yes
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break	Yes Yes Yes No
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • Monitoring of the supply voltage (PWR-LED)	Yes Yes Yes No No
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • Monitoring of the supply voltage (PWR-LED) • Channel status display	Yes Yes Yes No No Yes; green PWR LED
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • Monitoring of the supply voltage (PWR-LED)	Yes Yes Yes No No Yes; green PWR LED Yes; Green LED
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • Monitoring of the supply voltage (PWR-LED) • Channel status display • for channel diagnostics • for module diagnostics	Yes Yes Yes No No Yes; green PWR LED Yes; Green LED No
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • Monitoring of the supply voltage (PWR-LED) • Channel status display • for channel diagnostics • for module diagnostics	Yes Yes Yes No No Yes; green PWR LED Yes; Green LED No
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • Monitoring of the supply voltage (PWR-LED) • Channel status display • for channel diagnostics • for module diagnostics • Potential separation Potential separation channels	Yes Yes Yes No No Yes; green PWR LED Yes; Green LED No Yes; green/red DIAG LED
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • Monitoring of the supply voltage (PWR-LED) • Channel status display • for channel diagnostics • for module diagnostics • for module diagnostics • between the channels	Yes Yes Yes No No Yes; green PWR LED Yes; Green LED No Yes; green/red DIAG LED
Diagnostics function Substitute values connectable Alarms • Diagnostic alarm Diagnostic messages • Monitoring the supply voltage • Wire-break • Short-circuit Diagnostics indication LED • Monitoring of the supply voltage (PWR-LED) • Channel status display • for channel diagnostics • for module diagnostics • Potential separation Potential separation channels	Yes Yes Yes No No Yes; green PWR LED Yes; Green LED No Yes; green/red DIAG LED

Isolation	
Isolation tested with	707 V DC (type test)
Ambient conditions Altitude during operation relating to sea level	
 Ambient air temperature-barometric pressure- 	On request: Ambient temperatures lower than 0 °C (without
altitude	condensation) and/or installation altitudes greater than 2 000 m
Dimensions	
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	20 a
Weight, approx.	30 g
last modified:	10/15/2018